

DIAMOND

钻石系列安装说明书

Diamond series installation instructions

直射/可调窄边		直射/可调无边	
系列	开孔尺寸	系列	开孔尺寸
DR02301	Ø75mm	DR02303	Ø75mm
DR02302	Ø75mm	DR02304	Ø75mm
DR02305	Ø75mm	DR02307	Ø75mm
DR02306	Ø75mm	DR02308	Ø75mm
DR02309	Ø100mm	DR02311	Ø100mm
DR02310	Ø100mm	DR02312	Ø100mm
DR02313	Ø100mm	DR02315	Ø100mm
DR02314	Ø100mm	DR02316	Ø100mm
DR02317	Ø125mm	DR02319	Ø125mm
DR02318	Ø125mm	DR02320	Ø125mm
DR02321	Ø125mm	DR02323	Ø125mm
DR02322	Ø125mm	DR02324	Ø125mm

安装步骤一(窄边框弹片安装):
具体外观以实物为准!

1.1 在天花板安装位置根据型号对应的开孔尺寸开孔(适用天花板厚度2-20mm)。

1.2 断电情况下, 将驱动端电源线接市电(不含驱动需先接适配恒流驱动)。

1.3 整理好电源线, 将驱动置入天花孔内。

1.4 按压弹片, 把灯体卡入天花孔, 安装完成。

安装步骤二(预埋件安装):

2.1 在天花板安装位置根据型号对应的开孔尺寸开孔(适用天花板厚度2-20mm)。

2.2 可提前安装外环在天花孔内

2.3 先将反射器装在旋转环上






2.4 断电情况下, 引出电源线, 将驱动端电源线接市电(不含驱动需先接适配恒流驱动)。

2.5 将灯具向上推, 卡入外环内, 安装完成

灯具拆卸:
断电后, ①扣下反射器 ②抓住拉环向下拉出灯具

安装步骤三(无边预埋件安装):

预埋件需在批灰前安装好.



不要用手或者毛巾拭擦芯片与反射器!
Do not clean LED chip and reflector with hand or towel!



- 只能使用符合IEC或CCC安全标准的电源;
- 检查电源是否匹配灯具;
- 须考虑到最大电流值;
- 灯具上显示电压不是用来选择恒压电源, 而是表示所选择恒流电源所覆盖的电压;
- 采用合适的ESD措施, 避免触摸裸导体;
- 若与某种化学物质或气体接触, LED芯片会受损;
- 因此不能用化学物质清理LED壳体或LED驱动灯, 如下物质证实对灯具的性能有负面影响, 不能与LED灯具处在同一环境下.

指甲油
超能胶水
乙二醇
甲醛
LOCTITE胶水
漂白粉, 含漂白粉的清洁剂、喷雾剂
LOCTITE 384胶
LOCTITE 7387 活化剂

- 将绝缘物移开或提供足够空间以便灯具本身的温升不会超过额定的;
- LED芯片对开关瞬态很敏感, 因此LED灯具与电器必须在断电状态下连接, 不可热插拔.
- VF建议使用灯具说明书上指示的电源.
- 须顾及到产品的极性.
- 室内灯具建议使用环境温度-10° C-40° C
- 如果此灯具的外部软缆或软线损坏了, 该线要由制造商或其服务代理商或有类似资格的人更换
- 此灯具内的光源应由制造商或其服务代理商或有类似资格的人来更换


5.

6.

- Use only drivers that comply with IEC or CCC safety standards.
- Check if the power supply match with the luminaire.
- Must consider the maximum current value displayed on the label of the luminaire.
- The voltage displayed on the luminaire is not used to select the constant voltage driver, but the voltage covered by the selected constant current driver.
- Take suitable ESD measures to avoid touching bare conductors.
- LED chips can be damaged if be in touch with chemical material or gas. Therefore, it is not allowed to clean the LED housing or luminaire by chemicals.
- The following items are confirmed to have negative impact on the performance of the luminaire, avoid to keep luminaire in the same circumstance with them.
 - Methyl acetate or ethyl acetate (i.e., nail polish remover)
 - Cyanoacrylates (i.e., "Superglue")
 - Glycol ethers (including Radio Shack ® Precision Electronics Cleaner - dipropylene glycol monomethyl ether)
 - Formaldehyde or butadiene (including Ashland PLIOBOND ® adhesive)
 - Dymax 984-LVUF conformal coating
 - Loctite Sumo Glue, Loctite 384 adhesive, Loctite 7387 activator
 - Gorilla Glue, Bleach, Bleach-containing cleaners, sprays

- Remove the insulation material from the luminaire or provide enough space so that the temperature raising will not overpass the limited TC.
- LED chip is very sensitive to switching transients, therefore, LED lamps and appliances must be connected after power cut off, no hotswappable.
- VF recommends using the driver indicated on the luminaire manual.
- Must consider the polarity of the product.
- It is recommended to use an ambient temperature of -10 ° C to 40 ° C for indoor lighting equipment
- If the external flexible cable or cord of this lamp is damaged, the cord should be replaced by the manufacturer or its service agent or a similarly qualified person
- The light source in this lamp should be replaced by the manufacturer or its service agent or a similarly qualified person

7.



- 该产品只能安装在室内环境, 不能与水接触。
This product is only suitable for indoor, it is not allowed to be rinsed with water.
- 外置LED驱动, 嵌入式安装。
Independent external driver, recessed mounted.

爱加照明科技有限公司

广东省东莞市大朗镇洋乌村乌石岭三区438号

Tel: 0769-8539 7723 / 8539 7729 Fax: 0769-8258 3418
E-mail: info@vflighting.com Http: //www.vflighting.com

8.